

### Stereo Computer Headset Model NC-65



- **Andrea Noise Canceling Microphone Technology**
- **Soft Flex Microphone Boom**
- **Pre-Equalized CD Quality Sound**
- **High Quality Earphones with Large Comfortable Ear Cushions**
- **Stainless Steel Adjustable Headband**
- **Extra Long 8 Foot Shielded Cord**
- **For Left or Right Side Use**

Parameter	Value
<b>Microphone</b>	
Noise Cancellation	5 dB/octave
Frequency Range	100-10,000 Hz
Impedance at 1 kHz	
SoundBlaster Interface	400 ohm
Andrea Preferred Interface	1200 ohm
Electrical Signal-to-Noise Ratio	>60 dB
Sensitivity at 1 kHz (0 dB = 1 V/Pa)	
SoundBlaster Interface	-36 dB
Andrea Preferred Interface	-28 dB
Current Consumption	
SoundBlaster Interface	0.600 mA
Andrea Preferred Interface	0.100 mA
<b>Headphone Speaker</b>	
Frequency Range	50-20,000 Hz
Coil Resistance	32 ohm
Sound Output from 1 kHz 0.1 V Peak	82 dB
Input (0 dB = 20 µPa)	
Max. Input Power	100 mW